

APPLICATION FOR UNITED STATES LETTER PATENT
FOR
METHOD AND APPARATUS TO MODIFY POWER
REQUIREMENTS FOR A SYSTEM

Inventor(s): Paul M. Cohen
Christopher A. Meredith
Ronald J. Child

Prepared By: John F. Kacvinsky
Senior Patent Attorney

intel.

Intel Corporation
3500 Brooktree Road, Suite 100
Wexford, PA 15090
Phone: (724) 933-3387
Facsimile: (724) 933-3350

"Express Mail" label number EL034437435US

**METHOD AND APPARATUS TO MODIFY POWER
REQUIREMENTS FOR A SYSTEM**

5 BACKGROUND

A system may comprise a plurality of components, with each component having a certain power requirement. This power requirement may be in the form of an operating voltage, which is typically expressed in the form of volts. For example, the typical
10 operating voltage of a Pentium® III processor made by Intel® Corporation may be 1.6 volts. The power may be received from a shared system power supply that may provide power in the form of alternating current (AC) or direct current (DC). The system power supply may in turn receive its power from a larger power provider, such as a power generation grid or bank of batteries.

15 Power conditions for the system power supply and the larger power provider may change over time. For example, demand for power from the larger power provider may increase, thereby reducing the amount of available power to the system power supply. It may be desirable, therefore, to change the power requirement for one or more devices within a system using power from the system power supply in response to a change in
20 power conditions.

BRIEF DESCRIPTION OF THE DRAWINGS

The subject matter regarded as embodiments of the invention is particularly
25 pointed out and distinctly claimed in the concluding portion of the specification.

Embodiments of the invention, however, both as to organization and method of operation, together with objects, features, and advantages thereof, may best be understood by reference to the following detailed description when read with the accompanying drawings in which:

5 FIG. 1 is a system suitable for practicing one embodiment of the invention.

FIG. 2 is a block diagram of a system in accordance with one embodiment of the invention.

FIG. 3 is a block diagram of a system power modification unit in accordance with one embodiment of the invention.

10 FIG. 4 is a block flow diagram of operations performed by a system power modification unit in accordance with one embodiment of the invention.

DETAILED DESCRIPTION

15 In the following detailed description, numerous specific details are set forth in order to provide a thorough understanding of the embodiments of the invention. It will be understood by those skilled in the art, however, that the embodiments of the invention may be practiced without these specific details. In other instances, well-known methods, procedures, components and circuits have not been described in detail so as not to
20 obscure the embodiments of the invention.

A typical system may comprise a number of electronic devices or components that operate at certain operating power levels. Further, the devices may draw power from a common power supply. This may be the case, for example, when a number of network

devices are stored in the same physical rack. The proximity and power requirements for each device may facilitate the use of the single power supply, with each device having its own power connection to the system power supply. The system power supply may in turn be connected to a larger power supply, such as a plug providing AC power from a power generation grid or a bank of batteries providing DC power.

A problem may occur, however, whenever there are changes in power levels provided by the power supply, either at the system level power supply or the larger power supply. This typically occurs whenever the demand for power increases dramatically in an area serviced by the larger power supply. Demand may increase, for example, during the summer months due to an increase in the use of air conditioners that may draw power from a common power generation grid. The increase in demand may sometimes create a condition referred to as a power "brownout" or "blackout," where certain areas are left without power or reduced power. A reduction in the larger power supply may cause a reduction in the system power supply. A reduction in the system power supply may in turn affect performance of the entire system, including each device connected to the system power supply. For example, the reduction in power may cause the power provided to some or all of the devices connected to the system power supply to fall below the operating power levels of such devices, thereby causing the devices to potentially shut down. This shut down may occur to the entire system or parts of the system randomly, and without any regard to the functions provided by each respective device.

Furthermore, the shut down may occur to the entire system, even though the reduction in power is still sufficient to power each device at a lower power level, or a subset of system devices at the same or lower power levels.

The embodiments of the invention comprise a method and apparatus to modify power requirements for a system based on power conditions. In one embodiment of the invention, a system power modification unit may monitor the power level of a system power supply and modify the operating power levels for various devices within the system based on changes to the power supply power level. In one embodiment of the invention, the system power modification unit may comprise a power sensor and a power modification signal generator. The power sensor may monitor the power levels of the power supply. The power modification signal generator may generate a modification signal to modify the operating power levels of one or more devices within the system in accordance with changes detected by the power sensor. A device power modification unit may receive the modification signal, and modify the operating power levels of a device in accordance with the modification signal. The amount of modification may vary, and may be indicated by the modification signal itself, or by a value for each of the system devices as stored in a power table.

As a result of this embodiment of the invention, the operating power levels for one or more devices within the system may be lowered to compensate for the lower power levels from the system power supply. Furthermore, the amount of reduction may be regulated for each device or the system as a whole. In the event the power supply power levels are reduced to the point where some system devices need to be turned off, the embodiments of the invention may turn off each device in accordance with a priority level assigned each device. In this way those devices performing the most critical system functions may continue to provide those critical functions until system power levels either return to normal levels or force the entire system to shut down.

It is worthy to note that any reference in the specification to “one embodiment” or “an embodiment” means that a particular feature, structure, or characteristic described in connection with the embodiment is included in at least one embodiment of the invention. The appearances of the phrase “in one embodiment” in various places in the specification
5 are not necessarily all referring to the same embodiment.

Referring now in detail to the drawings wherein like parts are designated by like reference numerals throughout, there is illustrated in FIG. 1 a system suitable for practicing one embodiment of the invention. FIG. 1 is a block diagram of a system 100 comprising a power supply 102, a power modification unit 104, and a plurality of
10 electronic devices 106, 108, 110 and 112. Electronic devices may include any type of device that consumes or requires power. In one embodiment of the invention, electronic devices may include, for example, network devices, such as servers, network appliances, routers, switches, gateways, bridges, telephony, network processors, and so forth.

Additional devices may comprise, for example, personal computers (PC), storage devices
15 such as hard drives and optical drives, memory, specialized processors, network interface cards (NICs), physical interface cards (PICs) or any other electronic device or component that consumes power. Examples of additional systems other than system 100 that may be suitable for use with one or more embodiments of the invention may include a storage area network (SAN), local area network (LAN), wide area network (WAN), metropolitan
20 area network (MAN), a server farm, multiple servers or other systems having a plurality of devices sharing the same power supply. Power supply 102 is connected to system power modification unit 104, and both are connected to each of devices 106, 108, 110 and 112, respectively.

In operation, each device 106, 108, 110 and 112 has an operating power level. The operating power level for each device may be the same or different from the other devices. Each device draws power from power supply 102 according to its particular operating power level requirements.

5 System power modification unit 104 monitors power supply 102 for changes in power levels. If system power modification unit 104 detects a change in power levels for power supply 102, it may generate a modification signal. The modification signal may indicate to one or more devices to modify its operating power levels. The modification signal may be sent to each system device. Each system device may then modify its
10 operating power levels in accordance with the modification signal.

 There are several ways in which the operating power levels of a device may be modified. In one embodiment of the invention, the amount of modification may be predetermined. For example, if a device had a plurality of predefined operating power levels, the modification signal may indicate which level the device may use. In this
15 example, if the device had only two predefined operating power levels, the modification signal may cause the device to switch between the two operating power levels. In this embodiment of the invention, the presence of the modification signal may be sufficient to cause the device to switch between operating power levels. If the device had three or more predefined operating power levels, the modification signal may also indicate which
20 operating power level the device should use.

 In another embodiment of the invention, a device may not have predefined levels of operating power levels. For example, the device may have a minimum operating power level, but may operate at various levels of efficiency above this minimum

operating power level based on the amount of available power. In this case, the modification signal may indicate an amount by which the device should modify its current operating power level. The modification signal may also indicate whether the device should increase or decrease its current operating power level by the received amount.

FIG. 2 is a block diagram of a system in accordance with one embodiment of the invention. FIG. 2 illustrates a system 200. System 200 may comprise a system power modification unit 202 and a device power modification unit 208. System power modification unit 202 may be representative of, for example, system power modification unit 104. Device power modification unit 208 may comprise a part of each system device, such as system devices 106, 108, 110 and 112, for example. Device power modification unit 308 may also be a single component connected to and shared by system devices 106, 108, 110 and 112.

As shown in FIG. 2, system power modification unit may comprise a power sensor 204 and a power modification signal generator 206. Power sensor 204 may be connected to a power supply to monitor power levels for the power supply. An example of a power supply might be power supply 102. Power sensor 204 may receive signals from the power supply on a continuous or periodic basis. Power sensor 204 may be configured to detect changes in the power levels of the power supply by sampling the received signals. Power sensor 204 may also be configured to detect an amount of change in the power level of the power supply. The change may be measured several ways, such as against a predefined power level for the power supply, a measured average power level over a certain time period for the power supply, one or more previous

samples, and so forth. The change may be represented as an absolute or percentage value, depending on a particular system design. In one embodiment of the invention, the power sensor may detect the current power level of the power supply rather than the amount of change in the power level of the power supply.

5 Once power sensor 204 detects a change in power supply power levels, power sensor 204 may send a signal to power modification signal generator 306. In one embodiment of the invention, the signal may indicate a change in power levels for the power supply. In another embodiment of the invention, the signal may also include an indication of the amount of change in power as well, for example. In yet another
10 embodiment of the invention, the signal may also include an indication of the current power level of the power supply.

 Power modification signal generator 306 may operate to receive the signal from power sensor 304. Power modification signal generator 306 may then generate a modification signal based on the signal, including the indicator for the amount of change
15 in power levels, or the current power level of the power supply, if included.

 Power modification signal generator 306 may be configured to generate the modification signal in a number of desired ways. In one embodiment of the invention, power modification signal generator 306 may generate the modification signal to indicate each device should reduce its operating power levels by the same amount. The amount
20 may be calculated by power modification signal generator 306 based on a predetermined formula using the signal from power sensor 304 as partial inputs. The amount may also be retrieved from a power table. The power table may have predetermined reduction in power levels associated with each device based on the change in power levels in the

power supply or the current power level of the power supply. In one embodiment of the invention, power modification signal generator may receive the signal from power sensor 304, retrieve the amount of change in power levels from the signal, and search the power table by the amount of change in power levels. In this embodiment of the invention, the power table may have a predefined value associated with each change in power level, with the predefined value representing the amount of modification required for all devices within the system. In one embodiment of the invention, the value may be a percentage of the amount of change in power levels of the power supply. In another embodiment of the invention, the value may be an absolute value associated with each change in power level.

In one embodiment of the invention, the power table may be organized, managed and searched based on the current power level of the power supply as well. The power table may have a list of devices, and associated operating power levels, organized by the potential currently power level of the power supply. In this case, power sensor 304 may determine the current power level of the power supply, and provide this information to power modification signal generator 306. Power modification signal generator 306 may then search the power table by the current power level of the power supply, and retrieve a list of devices and their associated operating power levels. The modification signal may provide this information to the list of devices, and each device may ensure that they are operating at the appropriate operating power level.

In one embodiment of the invention, power modification signal generator 306 may generate the modification signal to indicate that some or all of the system devices need to modify its operating power level by varying amounts. The power table may be

organized by changes in power levels of the power supply or by the current power level of the power supply, with each change in power level or current power level having a corresponding number of devices that may need modifications to their operating power levels, and the amount of modification desired. Power modification signal generator 306
5 may select the corresponding number of devices randomly, or by an order of priority as set forth in the power table. The order of priority may be based on any number of factors, including the type of functions performed by the device, the operating power levels for the device, the capability of performing on reduced operating power levels for the device, the need of the device, and so forth. In addition, the selection of devices as set forth in
10 the power table may be updated according to external factors, such as time of day, date, current draw of operating power, and so forth. For example, some devices may be more critical during the day rather than the night. In such a case, the power table may have a value associated with the time of day. In another example, some devices may be more critical during certain periods of the month. In such a case, the power table may have a
15 value associated with the date or season.

Device power modification unit 308 may be configured to receive the modification signal, and modify the operating power levels of two or more devices in accordance with the modification signal. An example of a device power modification unit 308 may comprise, for example, a device power modification unit based on the
20 SpeedStep™ technology as built into the Pentium III mobile processors made by Intel Corporation. In one embodiment of the invention, the SpeedStep technology allows a mobile Pentium III processor to switch between performance modes. The switch between performance modes may be automatic based on the modification signal, or may

be manually configured by a user. For example, in one performance mode the processor may operate at a speed of 700 megahertz (MHz), and an operating voltage of 1.6 volts.

In another performance mode, the processor may operate at a speed of 600 MHz with an operating voltage of 1.35 volts. In another performance mode, the processor may draw

5 even less power based on the level of activity of the processor. For example, in this mode the power requirements may be less than half a watt when the processor is inactive or when transitioning between performance modes. In another example, the processor may be placed in a “deep sleep” mode wherein the current configuration of the processor or device using the processor is saved and the processor is basically suspended until the
10 operating power level may be increased to “reactivate” the processor. It can be appreciated that the Intel SpeedStep technology is only one example of the technology applicable for use as device power modification unit 308, and other technologies may be employed to modify the operating power levels of a device in accordance with a modification signal and still fall within the scope of the embodiments of the invention.

15 FIG. 3 is a block diagram of a system power modification unit in accordance with one embodiment of the invention. FIG. 3 may illustrate a system 300 that may be representative of a system power modification unit in accordance with one embodiment of the invention. In this embodiment of the invention, system power modification unit 300 may be implemented in software. It can be appreciated, however, that the
20 functionality for a system power modification unit may be implemented in hardware, software, or a combination of both, using conventional digital signal processing techniques.

FIG 3 illustrates a system 300 that may include a processor 302, an input/output (I/O) adapter 304, an operator interface 306, a memory 310 and a disk storage 318.

Memory 310 may store computer program instructions and data. The term “program instructions” may include computer code segments comprising words, values and

5 symbols from a predefined computer language that, when placed in combination according to a predefined manner or syntax, cause a processor to perform a certain function. Examples of a computer language may include C, C++, JAVA and assembly. Processor 302 executes the program instructions, and processes the data, stored in memory 310. Disk storage 318 stores data to be transferred to and from memory 310.

10 I/O adapter 304 communicates with other devices and transfers data in and out of the computer system over connection 324. Operator interface 306 may interface with a system operator by accepting commands and providing status information. All these elements are interconnected by bus 308, which allows data to be intercommunicated between the elements. I/O adapter 304 represents one or more I/O adapters or network
15 interfaces that can connect to a network, such as a LAN or WAN. Therefore, connection 324 may represent a network or a direct connection to other equipment.

Processor 302 can be any type of processor capable of providing the speed and functionality required by the embodiments of the invention. For example, processor 302 could be a processor from family of processors made by Intel Corporation, Motorola
20 Incorporated, Sun Microsystems Incorporated, Compaq Computer Corporation and others. Processor 302 may also comprise a digital signal processor (DSP) and accompanying architecture, such as a DSP from Texas Instruments Incorporated.

In one embodiment of the invention, memory 310 and disk storage 318 may comprise a machine-readable medium and may include any medium capable of storing instructions adapted to be executed by a processor. Some examples of such media include, but are not limited to, read-only memory (ROM), random-access memory (RAM), programmable ROM, erasable programmable ROM, electronically erasable programmable ROM, dynamic RAM, magnetic disk (e.g., floppy disk and hard drive), optical disk (e.g., CD-ROM) and any other media that may store digital information. In one embodiment of the invention, the instructions are stored on the medium in a compressed and/or encrypted format. As used herein, the phrase “adapted to be executed by a processor” is meant to encompass instructions stored in a compressed and/or encrypted format, as well as instructions that have to be compiled or installed by an installer before being executed by the processor. Further, system 300 may contain various combinations of machine-readable storage devices through various I/O controllers, which are accessible by processor 302 and which are capable of storing a combination of computer program instructions and data.

Memory 310 is accessible by processor 302 over bus 308 and includes an operating system 316, a program partition 312 and a data partition 314. In one embodiment of the invention, operating system 316 may comprise an operating system sold by Microsoft Corporation, such as Microsoft Windows[®] 95, 98, 2000 and NT, for example. Program partition 312 stores and allows execution by processor 302 of program instructions that implement the functions of each respective system described herein. Data partition 314 is accessible by processor 302 and stores data used during the

execution of program instructions. Program files and data files may also be stored in memory 318 as part of program files 322 and data files 320, respectively, as needed.

In one embodiment of the invention, program partition 312 contains program instructions that will be collectively referred to herein as a system power modification unit module. This module may perform the function of generating the modification signal as described herein. Of course, the scope of the invention is not limited to this particular set of instructions.

I/O adapter 304 may comprise a network adapter or network interface card (NIC) configured to operate with any suitable technique for controlling communication signals between computer or network devices using a desired set of communications protocols, services and operating procedures, for example. I/O adapter 304 also includes appropriate connectors for connecting I/O adapter 304 with a suitable communications medium. I/O adapter 304 may receive communication signals over any suitable medium such as copper leads, twisted-pair wire, co-axial cable, fiber optics, radio frequencies, and so forth.

The operation of systems 100, 200 and 300 may be further described with reference to FIG. 4 and accompanying examples. Although FIG. 4 as presented herein may include a particular processing logic, it can be appreciated that the processing logic merely provides an example of how the general functionality described herein can be implemented. Further, each operation within a given processing logic does not necessarily have to be executed in the order presented unless otherwise indicated.

FIG. 4 is a block flow diagram of the programming logic performed by a system power modification unit module in accordance with one embodiment of the invention.

FIG. 4 illustrates a programming logic 400. FIG. 4 illustrates a method to modify power to a system. A power level for a power supply may be monitored at block 402. The power supply may provide power to a plurality of devices. Each device may have an operating power level. A change in the power level for the power supply may be
5 detected at block 404. A modification signal to modify an operating power level of at least one of the plurality of devices may be created at block 406. The modification signal may be sent to the at least one of the plurality of devices at block 408.

In one embodiment of the invention, the modification signal may be received by the at least one of the plurality devices. The receiving device may then modify its
10 operating power level in accordance with the modification signal. In one embodiment of the invention, the modification signal may indicate that the receiving device should reduce its operating power level. In another embodiment of the invention, the modification signal may indicate that the receiving device should increase its operating power level.

15 In one embodiment of the invention, the modification signal may be created as follows. A particular device may be selected to modify its operating power level. An amount to modify the operating power level may be determined. The modification signal to modify the operating power level of the selected device may be created using the determined amount.

20 In one embodiment of the invention, a device may be selected by detecting an amount of change in the power level for the power supply. The amount of change may be used to search a power table. The power table may have one or more devices associated with a particular amount of change. The associated devices may be retrieved

from the power table using the amount of change. In addition, the power table may have an amount to modify the operating power level of each device. Therefore, once the devices are selected, an amount to modify the operating power level for each selected device may also be retrieved from the power table.

5 In one embodiment of the invention, the devices selected for modification of their operating power levels may receive the modification signal. Each device may determine an amount to modify its operating power level. This determination may be made by information provided by the modification signal. This determination may also be made by information retrieved from memory, such as a power table for the devices. Each
10 device may then modify its operating power level in accordance with the determination.

The operation of systems 100, 200, 300 and the flow diagram shown in FIG. 4 may be better understood by way of example. In this example, power supply 102 of system 100 may provide power to devices 106, 108, 110 and 112. Power supply 102 may receive its power from a power generation grid through an AC outlet, for example.

15 System power modification unit 104 may monitor the power levels for power supply 102 via power sensor 204. Power sensor 204 may detect a drop in power level for power supply 102. The drop may occur for various reasons, such as a brownout condition in the power generation grid. Power sensor 204 may send a signal to power modification signal generator 206 of system power modification unit 104. The signal may indicate the drop
20 in power level for power supply 102.

Power modification signal generator 206 may generate a modification signal for one or more devices 106, 108, 110 or 112. In one example, assume that devices 106, 108, 110 and 112 have two operating power levels. Assume the first operating power

level is 1.6 volts, and the second operating power level is 1.35 volts. Power modification signal generator 206 may first determine which of devices 106, 108, 110 or 112 it will select to modify its operating power levels. It may utilize a power table to make this selection. An example of a power table is shown in Table 1.

5

TABLE 1

<u>Current Power Level</u>	<u>Devices</u>	<u>Operating Power Levels</u>
Power Level 1	106, 108, 110, 112	1.6 volts
Power Level 2	106, 108, 110 112	1.6 volts 1.35 volts
Power Level 3	106, 108 110, 112	1.6 volts 1.35 volts
Power Level 4	106 108, 110, 112	1.6 volts 1.35 volts
Power Level 5	106, 108, 110, 112	1.35 volts
Power Level 6	106, 108, 110 112	1.35 volts 0 volts (shut down)

As shown in Table 1, each power level from 1-6 may identify a set of devices and the appropriate operating power level for each device. In this example, power level 1 is the highest power level and power level 6 is the lowest power level for a power supply. Values for power levels 1-6 may be any range of values appropriate to a particular power supply. Power modification signal generator 206 may receive a signal from power sensor 204 indicating that a change in power level for power supply 102 has occurred. In addition, the signal may indicate that the current power level of the power supply is power level 3. Power modification signal generator 206 may search a power table such as Table 1 using power level 3. The power table indicates that at power level 3, devices 106 and 108 should have an operating power level of 1.6 volts, and devices 110 and 112

should have an operating power level of 1.35 volts. Power modification signal generator 206 may then generate a modification signal indicating the information retrieved from the power table. Power modification signal generator 206 may then send the modification signal to devices 106, 108, 110 and 112.

5 Device power modification unit 208 for devices 106, 108, 110 and 112 may receive the modification signal. Each device may then modify its operating power level in accordance with the modification signal. In this example, device power modification unit 208 for device 106 may determine from the modification signal that its current operating power level should be 1.6 volts. Device power modification unit 208 may then
10 instruct device 106 to increase or decrease its operating power level to 1.6 volts, depending on the current operating power level of device 106. For example, if the current operating power level of device 106 is 1.35 volts due to a previous decrease in operating power level, device 106 may increase its operating power level to 1.6 volts in accordance with the modification signal. Devices 108, 110 and 112 may operate
15 similarly in modifying their current operating power levels in accordance with the information provided by the modification signal.

 In the example of the power table given in Table 1, it may be worthy to note that power level 6 indicates that devices 106, 108 and 110 may need to operate at 1.35 volts, while device 112 may need to shut down entirely to reduce power requirements for
20 system 100. Power level 6 may indicate, for example, a power level incapable of sustaining all the devices of system 100, and therefore requiring certain devices to draw less power and for some devices no power at all. This may be an example of determining

the sequence of device power reductions and shut downs based on various predetermined factors, as reflected by the particular configuration of the power table.

While certain features of the embodiments of the invention have been illustrated as described herein, many modifications, substitutions, changes and equivalents will now
5 occur to those skilled in the art. It is, therefore, to be understood that the appended claims are intended to cover all such modifications and changes as fall within the true spirit of the embodiments of the invention.

1
2
3
4
5
6
7
8
9
10
11
12
13
14
15
16
17
18
19
20
21
22
23
24
25
26
27
28
29
30
31
32
33
34
35
36
37
38
39
40
41
42
43
44
45
46
47
48
49
50
51
52
53
54
55
56
57
58
59
60
61
62
63
64
65
66
67
68
69
70
71
72
73
74
75
76
77
78
79
80
81
82
83
84
85
86
87
88
89
90
91
92
93
94
95
96
97
98
99
100
101
102
103
104
105
106
107
108
109
110
111
112
113
114
115
116
117
118
119
120
121
122
123
124
125
126
127
128
129
130
131
132
133
134
135
136
137
138
139
140
141
142
143
144
145
146
147
148
149
150
151
152
153
154
155
156
157
158
159
160
161
162
163
164
165
166
167
168
169
170
171
172
173
174
175
176
177
178
179
180
181
182
183
184
185
186
187
188
189
190
191
192
193
194
195
196
197
198
199
200
201
202
203
204
205
206
207
208
209
210
211
212
213
214
215
216
217
218
219
220
221
222
223
224
225
226
227
228
229
230
231
232
233
234
235
236
237
238
239
240
241
242
243
244
245
246
247
248
249
250
251
252
253
254
255
256
257
258
259
260
261
262
263
264
265
266
267
268
269
270
271
272
273
274
275
276
277
278
279
280
281
282
283
284
285
286
287
288
289
290
291
292
293
294
295
296
297
298
299
300
301
302
303
304
305
306
307
308
309
310
311
312
313
314
315
316
317
318
319
320
321
322
323
324
325
326
327
328
329
330
331
332
333
334
335
336
337
338
339
340
341
342
343
344
345
346
347
348
349
350
351
352
353
354
355
356
357
358
359
360
361
362
363
364
365
366
367
368
369
370
371
372
373
374
375
376
377
378
379
380
381
382
383
384
385
386
387
388
389
390
391
392
393
394
395
396
397
398
399
400
401
402
403
404
405
406
407
408
409
410
411
412
413
414
415
416
417
418
419
420
421
422
423
424
425
426
427
428
429
430
431
432
433
434
435
436
437
438
439
440
441
442
443
444
445
446
447
448
449
450
451
452
453
454
455
456
457
458
459
460
461
462
463
464
465
466
467
468
469
470
471
472
473
474
475
476
477
478
479
480
481
482
483
484
485
486
487
488
489
490
491
492
493
494
495
496
497
498
499
500
501
502
503
504
505
506
507
508
509
510
511
512
513
514
515
516
517
518
519
520
521
522
523
524
525
526
527
528
529
530
531
532
533
534
535
536
537
538
539
540
541
542
543
544
545
546
547
548
549
550
551
552
553
554
555
556
557
558
559
560
561
562
563
564
565
566
567
568
569
570
571
572
573
574
575
576
577
578
579
580
581
582
583
584
585
586
587
588
589
590
591
592
593
594
595
596
597
598
599
600
601
602
603
604
605
606
607
608
609
610
611
612
613
614
615
616
617
618
619
620
621
622
623
624
625
626
627
628
629
630
631
632
633
634
635
636
637
638
639
640
641
642
643
644
645
646
647
648
649
650
651
652
653
654
655
656
657
658
659
660
661
662
663
664
665
666
667
668
669
670
671
672
673
674
675
676
677
678
679
680
681
682
683
684
685
686
687
688
689
690
691
692
693
694
695
696
697
698
699
700
701
702
703
704
705
706
707
708
709
710
711
712
713
714
715
716
717
718
719
720
721
722
723
724
725
726
727
728
729
730
731
732
733
734
735
736
737
738
739
740
741
742
743
744
745
746
747
748
749
750
751
752
753
754
755
756
757
758
759
760
761
762
763
764
765
766
767
768
769
770
771
772
773
774
775
776
777
778
779
780
781
782
783
784
785
786
787
788
789
790
791
792
793
794
795
796
797
798
799
800
801
802
803
804
805
806
807
808
809
810
811
812
813
814
815
816
817
818
819
820
821
822
823
824
825
826
827
828
829
830
831
832
833
834
835
836
837
838
839
840
841
842
843
844
845
846
847
848
849
850
851
852
853
854
855
856
857
858
859
860
861
862
863
864
865
866
867
868
869
870
871
872
873
874
875
876
877
878
879
880
881
882
883
884
885
886
887
888
889
890
891
892
893
894
895
896
897
898
899
900
901
902
903
904
905
906
907
908
909
910
911
912
913
914
915
916
917
918
919
920
921
922
923
924
925
926
927
928
929
930
931
932
933
934
935
936
937
938
939
940
941
942
943
944
945
946
947
948
949
950
951
952
953
954
955
956
957
958
959
960
961
962
963
964
965
966
967
968
969
970
971
972
973
974
975
976
977
978
979
980
981
982
983
984
985
986
987
988
989
990
991
992
993
994
995
996
997
998
999
1000
1001
1002
1003
1004
1005
1006
1007
1008
1009
1010
1011
1012
1013
1014
1015
1016
1017
1018
1019
1020
1021
1022
1023
1024
1025
1026
1027
1028
1029
1030
1031
1032
1033
1034
1035
1036
1037
1038
1039
1040
1041
1042
1043
1044
1045
1046
1047
1048
1049
1050
1051
1052
1053
1054
1055
1056
1057
1058
1059
1060
1061
1062
1063
1064
1065
1066
1067
1068
1069
1070
1071
1072
1073
1074
1075
1076
1077
1078
1079
1080
1081
1082
1083
1084
1085
1086
1087
1088
1089
1090
1091
1092
1093
1094
1095
1096
1097
1098
1099
1100
1101
1102
1103
1104
1105
1106
1107
1108
1109
1110
1111
1112
1113
1114
1115
1116
1117
1118
1119
1120
1121
1122
1123
1124
1125
1126
1127
1128
1129
1130
1131
1132
1133
1134
1135
1136
1137
1138
1139
1140
1141
1142
1143
1144
1145
1146
1147
1148
1149
1150
1151
1152
1153
1154
1155
1156
1157
1158
1159
1160
1161
1162
1163
1164
1165
1166
1167
1168
1169
1170
1171
1172
1173
1174
1175
1176
1177
1178
1179
1180
1181
1182
1183
1184
1185
1186
1187
1188
1189
1190
1191
1192
1193
1194
1195
1196
1197
1198
1199
1200
1201
1202
1203
1204
1205
1206
1207
1208
1209
1210
1211
1212
1213
1214
1215
1216
1217
1218
1219
1220
1221
1222
1223
1224
1225
1226
1227
1228
1229
1230
1231
1232
1233
1234
1235
1236
1237
1238
1239
1240
1241
1242
1243
1244
1245
1246
1247
1248
1249
1250
1251
1252
1253
1254
1255
1256
1257
1258
1259
1260
1261
1262
1263
1264
1265
1266
1267
1268
1269
1270
1271
1272
1273
1274
1275
1276
1277
1278
1279
1280
1281
1282
1283
1284
1285
1286
1287
1288
1289
1290
1291
1292
1293
1294
1295
1296
1297
1298
1299
1300
1301
1302
1303
1304
1305
1306
1307
1308
1309
1310
1311
1312
1313
1314
1315
1316
1317
1318
1319
1320
1321
1322
1323
1324
1325
1326
1327
1328
1329
1330
1331
1332
1333
1334
1335
1336
1337
1338
1339
1340
1341
1342
1343
1344
1345
1346
1347
1348
1349
1350
1351
1352
1353
1354
1355
1356
1357
1358
1359
1360
1361
1362
1363
1364
1365
1366
1367
1368
1369
1370
1371
1372
1373
1374
1375
1376
1377
1378
1379
1380
1381
1382
1383
1384
1385
1386
1387
1388
1389
1390
1391
1392
1393
1394
1395
1396
1397
1398
1399
1400
1401
1402
1403
1404
1405
1406
1407
1408
1409
1410
1411
1412
1413
1414
1415
1416
1417
1418
1419
1420
1421
1422
1423
1424
1425
1426
1427
1428
1429
1430
1431
1432
1433
1434
1435
1436
1437
1438
1439
1440
1441
1442
1443
1444
1445
1446
1447
1448
1449
1450
1451
1452
1453
1454
1455
1456
1457
1458
1459
1460
1461
1462
1463
1464
1465
1466
1467
1468
1469
1470
1471
1472
1473
1474
1475
1476
1477
1478
1479
1480
1481
1482
1483
1484
1485
1486
1487
1488
1489
1490
1491
1492
1493
1494
1495
1496
1497
1498
1499
1500
1501
1502
1503
1504
1505
1506
1507
1508
1509
1510
1511
1512
1513
1514
1515
1516
1517
1518
1519
1520
1521
1522
1523
1524
1525
1526
1527
1528
1529
1530
1531
1532
1533
1534
1535
1536
1537
1538
1539
1540
1541
1542
1543
1544
1545
1546
1547
1548
1549
1550
1551
1552
1553
1554
1555
1556
1557
1558
1559
1560
1561
1562
1563
1564
1565
1566
1567
1568
1569
1570
1571
1572
1573
1574
1575
1576
1577
1578
1579
1580
1581
1582
1583
1584
1585
1586
1587
1588
1589
1590
1591
1592
1593
1594
1595
1596
1597
1598
1599
1600
1601
1602
1603
1604
1605
1606
1607
1608
1609
1610
1611
1612
1613
1614
1615
1616
1617
1618
1619
1620
1621
1622
1623
1624
1625
1626
1627
1628
1629
1630
1631
1632
1633
1634
1635
1636
1637
1638
1639
1640
1641
1642
1643
1644
1645
1646
1647
1648
1649
1650
1651
1652
1653
1654
1655
1656
1657
1658
1659
1660
1661
1662
1663
1664
1665
1666
1667
1668
1669
1670
1671
1672
1673
1674
1675
1676
1677
1678
1679
1680
1681
1682
1683
1684
1685
1686
1687
1688
1689
1690
1691
1692
1693
1694
1695
1696
1697
1698
1699
1700
1701
1702
1703
1704
1705
1706
1707
1708
1709
1710
1711
1712
1713
1714
1715
1716
1717
1718
1719
1720
1721
1722
1723
1724
1725
1726
1727
1728
1729
1730
1731
1732
1733
1734
1735
1736
1737
1738
1739
1740
1741
1742
1743
1744
1745
1746
1747
1748
1749
1750
1751
1752
1753
1754
1755
1756
1757
1758
1759
1760
1761
1762
1763
1764
1765
1766
1767
1768
1769
1770
1771
1772
1773
1774
1775
1776
1777
1778
1779
1780
1781
1782
1783
1784
1785
1786
1787
1788
1789
1790
1791
1792
1793
1794
1795
1796
1797
1798
1799
1800
1801
1802
1803
1804
1805
1806
1807
1808
1809
1810
1811
1812
1813
1814
1815
1816
1817
1818
1819
1820
1821
1822
1823
1824
1825
1826
1827
1828
1829
1830
1831
1832
1833
1834
1835
1836
1837
1838
1839
1840
1841
1842
1843
1844
1845
1846
1847
1848
1849
1850
1851
1852
1853
1854
1855
1856
1857
1858
1859
1860
1861
1862
1863
1864
1865
1866
1867
1868
1869
1870
1871
1872
1873
1874
1875
1876
1877
1878
1879
1880
1881
1882
1883
1884
1885
1886
1887
1888
1889
1890
1891
1892
1893
1894
1895
1896
1897
1898
1899
1900
1901
1902
1903
1904
1905
1906
1907
1908
1909
1910
1911
1912
1913
1914
1915
1916
1917
1918
1919
1920
1921
1922
1923
1924
1925
1926
1927
1928
1929
1930
1931
1932
1933
1934
1935
1936
1937
1938
1939
1940
1941
1942
1943
1944
1945
1946
1947
1948
1949
1950
1951
1952
1953
1954
1955
1956
1957
1958
1959
1960
1961
1962
1963
1964
1965
1966
1967
1968
1969
1970
1971
1972
1973
1974
1975
1976
1977
1978
1979
1980
1981
1982
1983
1984
1985
1986
1987
1988
1989
1990
1991
1992
1993
1994
1995
1996
1997
1998
1999
2000
2001
2002
2003
2004
2005
2006
2007
2008
2009
2010
2011
2012
2013
2014
2015
2016
2017
2018
2019
2020
2021
2022
2023
2024
2025
2026
2027
2028
2029
2030
2031
2032
2033
2034
2035
2036
2037
2038
2039
2040
2041
2042
2043
2044
2045
2046
2047
2048
2049
2050
2051
2052
2053
2054
2055
2056
2057
2058
2059
2060
2061
2062
2063
2064
2065
2066
2067
2068
2069
2070
2071
2072
2073
2074
2075
2076
2077
2078
2079
2080
2081
2082
2083
2084
2085
2086
2087
2088
2089
2090
2091
2092
2093
2094
2095
2096
2097
2098
2099
2100
2101
2102
2103
2104
2105
2106
2107
2108
2109
2110
2111
2112
2113
2114
2115
2116
2117
2118
2119
2120
2121
2122
2123
2124
2125
2126
2127
2128
2129
2130
2131
2132
2133
2134
2135
2136
2137
2138
2139
2140
2141
2142
2143
2144
2145
2146
2147
2148
2149
2150
2151
2152
2153
2154
2155
2156
2157
2158
2159
2160
2161
2162
2163
2164
2165
2166
2167
2168
2169
2170
2171
2172
2173
2174
2175
2176
2177
2178
2179
2180
2181
2182
2183
2184
2185
2186
2187
2188
2189
2190
2191
2192
2193
2194
2195
2196
2197
2198
2199
2200
2201
2202
2203
2204
2205
2206
2207
2208